




6H6, 6H6-GT/G

6H6
6H6-GT/G

TWIN DIODE

Heater		Coated Unipotential Cathodes	
Voltage	6.3	a-c or d-c volts	
Current	0.3	amp.	
Direct Interelectrode Cap. ^o	<i>6H6</i>	<i>6H6-GT/G</i>	
Plate #1 to Cathode #1	3.0	3.0	μf
Plate #2 to Cathode #2	3.4	4.0	μf
Plate #1 to Plate #2	0.10 max.	0.10 max.	μf
Maximum Overall Length	1-3/4"	3-5/16"	
Maximum Seated Height	1-3/16"	2-3/4"	
Maximum Diameter	1-5/16"	1-5/16"	
Bulb	Metal Shell MT-8	T-9	
Base	{ Small Wafer { Octal 7-Pin	{ Intermed. Shell { Octal 7-Pin	
Basing Designation	7Q	G-7Q	
Pin 1	{ 6H6, Shell { 6H6-GT/G, Internal shield	Pin 4 - Cathode #2	
Pin 2 - Heater		Pin 5 - Plate #1	
Pin 3 - Plate #2		Pin 7 - Heater	
RCA Socket		Pin 8 - Cathode #1	
Mounting Position		Stock No. 9924	Any



BOTTOM VIEW

Maximum Ratings Are Design-Center Values

RECTIFIER OR DOUBLER

Peak Inverse Voltage		420 max. volts
Peak Plate Current per Plate		48 max. ma.
D-C Heater-Cathode Potential		330 max. volts
<i>As Half-Wave Rectifier:*</i>		
A-C Plate Voltage per Plate (RMS)	117	150 max. volts
Total Effect. Plate-Supply Impedance per Plate [▲]	15 min.	40 min. ohms
D-C Output Current per Plate	8 max.	8 max. ma.
<i>As Voltage Doubler:</i>		

	<i>Half-Wave</i>	<i>Full-Wave</i>
A-C Plate Voltage per Plate (RMS)	117	117 volts
Total Effect. Plate-Supply Impedance per Plate [▲]	30 min.	15 min. ohms
D-C Output Current	8 max.	8 max. ma.

^o With shell or external and internal shields connected to cathodes.
^{*} In half-wave service, the two units may be used separately or in parallel.
[▲] When a filter-input condenser larger than 40 μf is used, it may be necessary to use more plate-supply impedance than the minimum value shown to limit the peak plate current to the rated value.

Circuits for the 6H6 and 6H6-GT/G are the same as those shown under Type 2525.

← Indicates a change.

AUG. 1, 1942

RCA RADITRON DIVISION
RCA MANUFACTURING COMPANY, INC.

DATA

6H6



6H6

AVERAGE CHARACTERISTICS

HALF-WAVE RECTIFICATION - SINGLE DIODE

